

MIXING AMPLIFIERS

MA Mixing Amplifiers

Compact size mixing amplifiers for music and speech.

MA 30X

30W power, low and high impedance outputs, microphone and line level signal inputs, tone control, microphone input priority and phantom power. Perfect for use in small size applications such as shops, bars or restaurants, and there's no need for professional installation assistance.



Technical Specifications	MA 30X
Output power	30 W
Phantom power	48 V
AC power supply	230 V AC, 50 Hz
Idle power consumption	7.3 W
Max power consumption	90 W
Outputs	Low impedance output: 4Ω / 8Ω Hi impedance: 70 V / 100 V
MIC inputs	Input 1 sensitivity: -51 dBu, connector: balanced XLR, priority, phantom power Input 2 sensitivity: -51 dBu, connector: balanced XLR Input 3 sensitivity: -51 dBu, connector: unbalanced TS
Line inputs	Input 2 sensitivity: -14 dBu, connector: balanced Phoenix Input 3 sensitivity: -20 dBu, connector: unbalanced stereo RCA
THD	1%
S/N ratio	55 dB
Frequency response	55 Hz - 20 kHz
Equalizer	Bass: 80 Hz ± 12 dB, Treble: 12 kHz ± 12 dB
Dimensions	280 mm x 233 mm x 75 mm
Weight	3.5 kg